



Our most advanced and versatile analog multi-satellite receiver. Thanks to the integrated decoder options (VC-1/D(2)Mac), there's a vast choice from the large and varied program offer.

The LT-8700 UHF with SatTrack receives all available satellite signals from 64 satellites.

Up to 1500 channels, with 200 favorite video's and 100 favorite audio's. With the UHF remote control, the satellite receiver can be operated from anywhere in the house.

The Wegener Panda option offers magnificent sound.

## LT-8700

### GENERAL

Parental lock	
Clock function	
Data transfer	
VCR back-up function	
Channels	1500
Favorite videos	200
Favorite audios	100
On Screen Graphics	English, German, French, Italian, Spanish
Frontpanel display	6 x 7 segment
Operating keys	On/standby, channel up/down
Video timer	8
Optional	VC-1/D(2) Mac decoders
Remote control	UHF 433 MHz

### TUNER

Receiving frequency	950 - 2050 MHz
Input connector	Dual input tuner
IF bandwidth	18/27 MHz
Tuning options	Direct frequency entry, free tunable, video scan
Polarity switching	ferrite, polarotor (Skew storeable per channel)
Band switching	13/18 V band selection, max 300 mA
Threshold	<4.0 dB, adjustable

### VIDEO

System	PAL/NTSC/Secam
Brightness control	C/Ku band
	4 levels

### AUDIO

Volume control and audio mute	
Range	5.00 - 8.50 MHz
Audio bandwidth	110, 150, 280, 400 kHz
Audio de-emphasis	50 µs, 75 µs, J17, adaptive
Optional	Panda Wegener

### BUILT-IN DECODER

Number of smart cards	1 for VC-1
	2 for D/D(2)Mac

### OUTPUTS

Scart sockets	TV, VCR
Phono Sockets	Audio left/right, baseband video, video out
	VCR out, external audio input, external video input, AGC output

0-12 V control	
UHF modulator	PAL B/G and I, CH 28 - 47

### POWER SUPPLY

Mains input range	176 - 265 Volt
Power consumption	220 Watt

### MECHANICS

Dimensions	430 x 360 x 65 mm
Weight	6.8 kg

# LT-8700

